



Powered by  
 **Perkins**<sup>®</sup>



[www.perfecthouseltd.in](http://www.perfecthouseltd.in)

## 600KVA SPECIFICATIONS

D.G. Set	Generating Set Model	PPER600	
	KVA/KW (Prime)	600/480	
	KVA/KW (Standby)	660/528	
	Frequency /RPM	50 Hz /1500, 60Hz/1800	
	Voltage / No. of Phase	415 / 3	
	Power Factor	0.8	
	Rated Current(Amps)	834	
	Over Load Capacity	10 % over Load for 1 Hours in each 12 Hour of Operation	
	Fuel Tank Capacity (liters)	820	
	Acoustic Enclosure Dimensions L x W x H (mm) (Approx)	5550 X 2000 X 2340	
	Gross weight (KG) (Approx)	7000	
Diesel Engine	Engine Make	PERKINS	
	Engine Model	2806D-E18TAG1A	
	Engine Power (bhp)	721	
	No. of Cylinders	6	
	Cycle (Stroke)	4 Stroke	
	Combustion System	Direct injection diesel	
	Compression Ration	18.0:1	
	Bore X Stroke (mm)	145 x 183 mm	
	Displacement (litres)	18.1 litres	
	Fuel Consumption (Lit/ Hr) @ 100% Load	130	
	Fuel Consumption (Lit/ Hr) @75% Load	102	
	Cooling system	Liquid Cooed	
	Type of govermor	Electronic	
	Aspiration	Turbocharged and air-to-air charge cooled	
	Lube oil sump capacity (Liters.)	67 litres	
	Recommended Service Interval for Genset	500 Hours / 12 Month whichever is earlier	
	Coolant Capacity - UOM as Liters	61 litres	
	Recommended Coolant	Ethylene glycol base concentrate ideal mixing ratio of water to antifreeze is 50:50	
	Electrical System (12V/24V)	24V	
	No. of Battery	2	
Battery Capacity	150 AH		
Alternator	Alternator Make	Stamford	Leroy-Somer
	Alternator Model	HCI 534V/544V	LSA 47.2 M7
	Voltage	415 Vol / 230Vol	
	Frequency	50Hz	
	Class of Insulation	Class H	
	Power Factor	0.8	
	Pole	4 Pole	
	Voltage Regulation	± 1% AVR (Automatic Voltage Regulator)	
Panel	IP Rating	IP 23	
	Controller	Deep Sea 4520 MK II	
	Battery Charger	12 VDC, Automatic Battery Charger	

**\*\*Conformance Standards:** ▪ IS/IEC 60034-1 ▪ IS 8528 ▪ ISO 9001 ▪ ISO 1460 ▪ ISO 3046 ▪ ISO 13018 ▪ CE Comply/Approved

### Notes:

Specifications and dimensions are subjected to change without prior notice. Data is on NTP conditions as per ISO 3046.

+5% production tolerance is applicable as per ISO3046. Fuel consumption is based on diesel fuel with a specific gravity of 0.85 and confirming to BS 2869, Class A2) and standard alternator efficiency. The fuel consumption may vary depending upon the alternator. 4 Available with Voltage variation (230,380,400,440,460,480 etc.).

# DG CONTROL PANEL

## ▶ Operating Features

- Microprocessor based digital controller
- Accurate LCD display
- Local Start/Stop
- Remote Start/Stop
- Generator breaker control
- Easily Accessible through Fascia
- Flexibility for selecting Manual, Auto operations
- Easily Convertible AMF by giving Mains Fail Signal

## ▶ Metering

### Engine Parameters:

- Engine Speed
- Lube Oil pressure
- Coolant temperature
- Engine Running Hour
- Engine Battery voltage
- Running status
- Fuel level in Percentage
- Event Log with date and time

### Electrical Parameter

- Generator Voltage (Ph-Ph)
- Generator Voltage (Ph-N)
- Generator Current (R,Y,B)
- Generator Apparent power (kVA)
- Generator active power(kW)
- Generator reactive power (kVAr)
- Generator Power Factor
- Generator Frequency (Hz)
- Cumulative Power Consumption in kWh
- Cumulative Power Consumption in kVAh
- Cumulative Power Consumption in kVArh
- Control Supply Voltage

## ▶ Protection

### Engine

- High Water Temperature
- Low oil pressure
- Low Fuel Level
- Over Speed
- Engine Fails to Start

### Electrical

- Generator under Voltage (ANSI-27)
- Generator over Voltage (ANSI-59)
- Generator under Frequency (ANSI-81L)
- Generator over Frequency (ANSI-81H)
- Generator over Current (ANSI-51)
- Control Supply under Voltage
- Control Supply over Voltage
- Phase Reversal
- Unbalanced Load

## ▶ Controller

The DSE 4520 MKII Is A Compact Auto Mains (utility) Failure Control Module That Has Been Developed To Provide An Outstanding Range Of Features Within A Compact Enclosure.

The Module Can Be Configured For Use As An Auto Start Control Module.



## ▶ Controller Feature

- User-friendly interface and backlite full graphics LCD
- Battery voltage monitoring & reverse protection to aux supply
- 7/9 configurable analogue/digital inputs
- Auto, Manual and Remote Start/Stop Operation
- Island Operation
- Automatic Mains Failure Function
- CAN bus Engine interface for communication
- Log with latest 100 events
- Fully configurable via PC using USB, RS485 communication
- DC Battery supply voltage range 8 to 32V
- -20 to 65 °C operating temperature range
- Ip65 Protection class with gasket
- LCD alarm indication
- Power save mode
- 7 configurable Digital output

## ▶ Electrical Specification

- Supply Voltage Range: Nominal Voltage - 12/24 V DC
- Cranking drop out period: 50 ms
- Maximum reverse voltage protection: -32 V DC
- Measurement accuracy (battery voltage):  $\pm 1\%$  Full scale
- Resolution: 0.1 V
- Maximum current consumption  $\sim 200$  mA
- Measurement accuracy (battery voltage) -  $\pm 1\%$  full scale

## ▶ Environmental Specification

- Operating Temp: -20 to 65°C in compliance with 60068-2-1, 2
- Vibration: 2G in X, Y and Z axes for 8 to 500Hz in compliance with IEC 60068-2-6
- Shock: 15 g for 11 ms in compliance with IEC 60068-2-27
- Humidity: 0 to 95% RH in compliance with IEC 60068-2-78
- Protection Degree: IP65 Protection class with gasket in compliance with IEC60529
- EMI/EMC in compliance with IEC 61000-6-2, 4

## ▶ Approvals

- CE Compliant
- UL/cUL Recognized to UL/ulc6200:2019 1st edition



**60+**  
of  
Legacy

**5GW+**  
of Power  
Delivered

**Globally  
Certified**

**800+**  
Employees  
Across the Globe

**24,000** sq.ft  
Manufacturing Unit

**200,000+**  
Power Generators Supplied

**35+**  
Countries Powering Global  
Success



**Perfect House Pvt. Ltd.**

2nd Floor, 99C Kavya Aura, Next to Rosewood Hotel, Tardeo,  
Mumbai – 400034, India

Contact No: +9122-62611900/907

✉ exports@perfectgenset.com

**Factories**

Plot no. M-7, J-2/5, J-2/6, J-10,  
Additional MIDC, Satara -415004, India